

Call History Pro - Version 1.1

- 1) Install the two prc files on to your Kyocera QCP -6035 Phone.
- 2) Run Phone Tools Pro and select Preferences from the main menu.
- 3) Set the starting day of your current billing cycle.
- 4) Set the starting time of your billing cycle (12:01AM for Sprint);
- 5) To configure your plan details tap Peak or the Off Peak button.
- 6) Set your Peak minutes that are included in your plan.
- 7) Set your Off Peak minutes that are included in your plan.
(If you have none set the Off Peak Min to 0)
- 8) From the Select Days pop up list, select Set all Days. This will set all the days' peak time, off peak time and costs for all the days of the week.

Please note, you can set the cost by day for each plan. The “Set All Days” options is just a short cut to set all the rates the same for all the days.

- 7) Tap “(1) Set” to set your Peak minute cost for the minutes in excess of what is included in your plan.
- 8) Tap “(2) Set” to set your Off Peak minute cost for the minutes in excess of what is included in your plan. (If you have none set the Off Peak \$ Min to 0)
- 9) Tap “(3) Tap to Set” to set your Peak minute period. This will set the peak time period and cost for all the days of the week. Note, the Off Peak period is automatically set as the period outside of the Peak period you define.
- 10) If you plan has a different rate structure for Weekends. Then using the “Select Days” pop up list. Select Saturday, from the list and set the “\$ Min” to your plans rate. Use 0 if you have an unlimited Weekends calling plan. Then do the same thing for Sunday.
- 11) If you have a plan that with the first incoming minute free then check the check the check box.
- 12) Tap save. Depending on your plan the display will show the number of minute followed by the cost for peak and off peek time. The cost will be the first non-zero valued entered for the days.
- 13) To configure your plan details for Mobile to Mobile, Tap the Mobile 2 Mobile button.
(If you have none set the M2M Min to 0)
- 14) From the Select Days pop up list, select Set all Days. This will set all the days' Mobile 2 Mobile time and costs for all the days of the week.
- 15) Tap “(1) Set” to set your Mobile 2 Mobile minute cost for the minutes in excess of what is included in your plan.
- 16) Tap “(2) Tap to Set” to set your Mobile 2 Mobile minute period. This will set the Mobile 2 Mobile time period and cost for all the days of the week.
- 17) If you leave the check box checked then at the end of each call you will be prompted to add the number called/calling to the Mobile 2 Mobile list. Once you have captured you M2M list you may wish to shut off this feature.
- 18) Tap save.

19) Tap save.

During this billing cycle the minutes used will be displayed. If you exceed your plans minutes for peak or the off peak calling periods the cost will be displayed in the cost column. At the end of the billing cycle Phone Tools - Call History Pro will automatically record your final total minutes and costs, for that billing cycle and begin displaying the new billing cycle's running totals.

Please note: The Phone Tools - Call History Pro reads the Kyocera's CallHistoryDB.pdb file. This file is created and maintained by the factory installed version of the Kyocera's Call History application. To get a somewhat more accurate time usage it is advisable to set the Maximum # of calls to 999. Please Use the Kyocera's Call History application to set this parameter. Select Call History->Options->Preferences to do so.

A word about accuracy:

The phone tracks the number of seconds used. Because of rounding this value is really far off from the actual billed minutes. Phone Tools - Call History Pro tries to make a more accurate calculation but it can not know certain pieces of information that the phone company knows. Like how many seconds elapsed between the person dialing your number and you answering.

As with all phone numbers entered into the Palm, It is recommended that you enter all 10 digits. So if you add numbers manually to the Mobile to Mobile list use the full 10 digit number. For example the number (808) 712-5555 in your M2M list will match 712-5555 and (808) 712-5555. However with 712-5555 in your M2M list it will only match 712-5555 and NOT (808) 712-5555.

Comments or questions:

Please email <mailto:Support@SmartPhoneTools.com>